

Fast Ethernet Bridge Media Converters



The PLANET FT-80X is Fast Ethernet Bridge 100Base-FX fiber to 10/100Base-TX shielded twisted pair (STP) converter. It supports selectable for half-duplex and full-duplex operations and supports a variety of fiber options. The converter auto-adapts to the highest level of performance supported by the device connected to the STP port. When the device is a switch or a workstation that supports full duplex, the converter adapts to the full-duplex mode and provides an effective 200Mbps bandwidth. When the connected device is a hub or a workstation that supports only half duplex, the converter adapts to the half-duplex mode and provides the nominal 100Mbps bandwidth. An override switch provides total manual control over the half/full-duplex operation, in fiber-optic interface. The fiber port of converter operates at 1310 nm and uses ST, SC, MT-RJ, VF-45 connectors. Multi-mode models that support distances up to 2 km and single-mode models that support distances up to 15/35/50 km are available.

The FT-80x series are with LFP (Link Fault Pass Through function) (LLCF/LLR) and the DIP Switch design. LLCF/LLR can immediately alarm administrators the problem of the link media and provide efficient solution to monitor the net. The DIP Switch provides disable or enable the LFP function.

LLCF (Link Loss Carry Forward) means when a device connected to the converter and the TP line loss the link, the converter's fiber will disconnect the link of transmit. LLR (Link Loss Return) means when a device connected to the converter and the fiber line loss the link, the converter's fiber will disconnect the link of transmit. Both can immediately alarm administrators the problem of the link media and provide efficient solution to monitor the net.

KEY FEATURE

- Comply with IEEE 802.3, IEEE 802.3u 10/100Base-TX, 100Base-FX Standard
- Connectors: One RJ-45 (Auto-MDI/MDI-X) Twisted Pair, EIA568
- One Fiber-optic, 1310nm wavelength, connector-type and distance vary with model.
- Data Transfer Rate:
 - TP: 10/100Mbps
 - FX: 100Mbps
- Duplex mode support: Full or half-duplex mode by Auto-Negotiation (TP)
- Full or half-duplex mode by DIP-switch (FX)
- LED indicators:
 - PWR, FX LNK/ACT, FX FDX/COL, TP 100, TP LNK/ACT, TP FDX/COL
- DIP-switch: 2 DIP-switches
 - Rear DIP-switch: FX duplex mode selection
 - Side DIP-switch: LFP (Link Fault Pass-through) mode selection

SPECIFICATION
Product Fast Ethernet Bridge Media Converters

Model	FT-80X series
Protocol	IEEE 802.3u, 100Base-FX, 10/100Base-TX
Dimensions	70 x 97 x 26 mm (W x D x H)
Weight	0.2kg
Power	5V DC, 2A, max.
Connectors and Cables	
Twisted Pair/STP	RJ45, Category 5 (EIA/TIA 568)
Fiber-optic	Vary on model; X=1,2,3,4 1:ST 2:SC 3:MT-RJ 4:VF-45
Multi-mode cable	50/125, 62.5/125 μ m
Single-Mode(SM) cable	9/125 μ m
Supported Distances and function	
Twisted Pair STP	100 m / 328 ft.
Multi-mode Fiber Optic	412 m / 1,350 ft. (Half-Duplex) 2 km / 1.2 mile. (Full-Duplex)
Single-Mode(SM)	412 m / 1,350 ft. (Half-Duplex) 15 km / 9 mile. (Full-Duplex) 35km / 21 mile. (Full-Duplex) 50km / 31 mile. (Full-Duplex)
Port Mode	TP: Half and Full Duplex, auto-negotiation FX: Half and Full Duplex via DIP switch
Environmental	
Temperature	0 to 50 Degrees C
Humidity	5-90% (non-condensing)

ORDERING INFORMATION

FT-801	100Base-FX to 10/100Base-TX (ST, MM) Bridge Media Converter
FT-802	100Base-FX to 10/100Base-TX (SC, MM) Bridge Media Converter
FT-802S15	100Base-FX to 10/100Base-TX (SC, SM, 15Km) Bridge Media Converter
FT-802S35	100Base-FX to 10/100Base-TX (SC, SM, 35Km) Bridge Media Converter
FT-802S50	100Base-FX to 10/100Base-TX (SC, SM, 50Km) Bridge Media Converter
FT-803	100Base-FX to 10/100Base-TX (MT-RJ, MM) Bridge Media Converter
FT-804	100Base-FX to 10/100Base-TX (VF-45, MM) Bridge Media Converter